



## YAS

Public Address - Amplifiers and Audio Sources

Mixer amplifier with built-in FM tuner and USB-MP3 player

### GENERAL FEATURES

3 models: YAS80 (80 W), YAS120 (120 W) and YAS240 (240 W)

Chime and siren function

3 AUX inputs, 2 MIC inputs, 1 AUX output

Individual control for MIC and AUX input

Master volume control

Bass and treble control

18x64 dots LCD

4 loop play modes for MP3 5 sound effects for user to choose

Remote control and stand by function

70 V, 100 V and 8 Ohm output

### TECHNICAL CHARACTERISTICS

|                            |  |
|----------------------------|--|
| <b>Power:</b>              | 80 W (YAS80), 120 W (YAS120), 240 W (YAS240)       |
| <b>Sound Output Level:</b> | AUX 600 Ohm / 1V (0dBV)                            |
| <b>Frequency Response:</b> | 100 Hz - 16 kHz                                    |
| <b>Signal/Noise Ratio:</b> | Mic 1,2: 66 dB - Aux: 70 dB                        |
| <b>Mains Input:</b>        | 230 V AC 50/60 Hz                                  |
| <b>Dimensions:</b>         | 487 x 70 x 310 mm                                  |
| <b>Weight:</b>             | 5.5 Kg (YAS80) - 7.0 Kg (YAS120) - 8.5 Kg (YAS240) |
| <b>Colours:</b>            | Black  |

### INSTALLATION

Rack mount or stand alone