



PCP1272

Background Music - Controls and Modules (45x45mm)

FM stereo control / tuner, with 1 stereo channel and message receipt. Infrared receiver, controlled by P4803 or P4804 remote control (optional). Permits storing up to 30 stations with functions: message receipt, superbass, sleep, adjustment of bass, treble, balance and ideal sound.

GENERAL FEATURES

- Electronic ON / OFF switch.
- ON /Sleep/ Sb luminous indicator, bicolour LED type.
- Key depression luminous indication (Vol+, Vol- and SCAN).
- 52-step digital volume control with selected position memory.
- Integrated audio processor.
- Superbass.
- SCAN function (change radio station of tuner or external device).
- Selection of external music channel or internal tuner, with luminous indication of selected audio source.
- Voltage telecontrol.
- External channel input (walkman).
- Direct access to stations via control P4804.
- Jumper for selection of mono output. For this type of installations place the jumper M/S.

TECHNICAL CHARACTERISTICS

Music channels:	1 + Sintonizador FM
Power:	1 + 1 W RMS
Output Impedance:	8 Ohm.
Maximum Power:	1.5 + 1.5 W RMS
Frequency Response:	80 Hz. - 21 KHz. (-3dB)
Signal/Noise Ratio:	> 87 dB
Crosstalk:	40 dB
Sensitivity:	(Terminales 15, 16) 1,45 V
Aux Input:	400 mV
Mains Input:	16 V DC
Nominal Input Level for Warning Switching:	15 V
Antenna Connector Input:	75 Ohm
Maximum Consumption:	420 mA
Standby Consumption:	30 mA
Dimensions:	45x45x45 mm.
Weight:	50 gr.
Colours:	PCP1272-01 (White), PCP1272-02 (Graphite), PCP1272-10 (Ivory), PCP1272-12 (Silver)

INSTALLATION