



PCP1273

Background Music - Controls and Modules (45x45mm)

FM stereo control / tuner, with 1 stereo channel and BLUETOOTH receiver. Permits storing up to 30 stations.

GENERAL FEATURES

Electronic ON / OFF switch.
ON / Sleep/ Sb luminous indicator, bicolour LED type.
Key depression luminous indication (Vol+, Vol- and SCAN)
52-step digital volume control with selected position memory.
Integrated audio processor.
Superbass.
SCAN function (change radio station of tuner)
Selection of external music channel, internal tuner or BLUETOOTH receiver, with light indicating selected audio source.
Voltage telecontrol.
Direct access to stations via SCAN pushbutton.
Jumper for selection of mono output. For this type of installations place the jumper M/S.

TECHNICAL CHARACTERISTICS

| | |
|---------------------------------|---|
| Music channels: | 1 + FM + BLUETOOTH |
| Power: | 1 + 1 W RMS |
| Output Impedance: | 8 Ohm. |
| Maximum Power: | 1.5 + 1.5 W RMS |
| Frequency Response: | 80 Hz. - 21 KHz. (-3dB) |
| Signal/Noise Ratio: | >87 dB |
| Crosstalk: | 40 dB |
| Sensitivity: | (Terminales 15, 16) 1,45 V. |
| Mains Input: | 15 V. |
| Antenna Connector Input: | 75 Ohm. |
| Maximum Consumption: | 470 mA |
| Standby Consumption: | 30 mA |
| Dimensions: | 45x45x45 mm. |
| Weight: | 50 gr. |
| Colours: | PCP1273-01 (White), PCP1273-02 (Anthracite grey), PCP1273-10 (Ivory), PCP1273-12 (Silver) |

INSTALLATION

- Universal box.
- A front plate with support is required. See accessories.