



P5552

Background Music - Call Console

Desk for announcement broadcast with general call and DIN-DON.

GENERAL FEATURES

- 'All' push button of General Call, and LED indicating hold (red) during the broadcast of the notice.
- Led (green) indicating connected microphone.
- 'Lock' push button for locking general call.
- Push buttons for calls to areas.
- 'On/off' switch for DING-DONG, with led indicating status.
- Front adjustment for level of broadcast of notices.
- Reset internal protection (Polyswitch) against short-circuits and inversion of supply polarity.
- 2 DB1 and DB2 rear connectors (type DB15) to allow an easy and quick connection to Sonelco line.
- Rear jack for supply with an external auxiliary supplier 15V/1A.
- Auxiliary audio exit of a Jack 6.35 type.
- Internal pre-adjusted adjustments from the factory for Ding-dong level and microphone sensibility.

TECHNICAL CHARACTERISTICS

Output Impedance: Sensitivity: Nominal Input Level for Warning Switching: Nominal Output Level for Calls: Maximum Consumption: Standby Consumption: Dimensions: Colours: 100 Ohm 5mV/1PSA V(Zi)= 15 V / Imax: 500 mA 3 Vrms 500 mA 25 mA 85x150x150 mm P5552-02 (Graphitie).

INSTALLATION

These features given for information only. Sonelco.com reserve the right to make changes without notice in order to improve the product. More information: (+34) 976 259 135 / (+34) 609 719 454 / sat@sonelco.com